

# Video & Optical Systems Limited

5-9 Cedar Court, Grove Park Industrial Estate, White Waltham, Maidenhead, Berkshire, SL6 3LW

Tel: +44 1628 829 356

Fax: +44 1628 824 316

Website: [www.video-optical.co.uk](http://www.video-optical.co.uk)

E-mail: [sales@video-optical.co.uk](mailto:sales@video-optical.co.uk)



## Police Body Worn Camera VOS-PBWC-2



### Features

- Built-In, Direction turn, Waterproof, Shockproof
- 80° field of view lens
- 2 pcs 3 core Highlight LED 20Lm Lumen
- 1.5 inch HD TFT
- High Sensitivity, High SNR, Omni bearing all-round sound pickup
- 12 hours stand by time
- Light weight only 170g
- -10°C ~60°C temperature range

### Specifications

Item	Specification
Camera	Built-in, Direction turn, waterproof, shockproof, antilog
Photo Resolution	5Mega pixels 2592* 1944 JPEG
Record Resolution	720 * 576
Video Compression	Standard MPEG4
Display	1.5inch HD TFT
LED	2 pcs 3core highlight LED 20Lm lumen
Lens Focus	f=6.089mm
Illumination	≥0.1LUX
Continuous Working Time	30F/S 8 H
Power Supply	Rechargeable lithium 3.7 V 2400mA
Wear Type	Shoulder Wear
Image	CMOS 5 Mega pixels (LED)
Record F/S	15F/S 25F/S 30F/S optional
Lens Angle	80°
Sound Pick-up	High sensitivity ; High SNR; Omni Bearing All-round Sound Pick-up
LED	8 pcs
Lens Aperture	F/3.25
Focus	0.5M—No limit
Standby Time	12 Hours
Storage	Misco TF (2-32G Optional)
Data Port	USB port , USB 2.0, battery charging
Work Temperature	-10°C —60°C
Mobile Work Type	Vehicle bracket and vehicle charger
Night	7—10M
Size	113 x 75 x 36mm
Weight	170g

## Main instructions

1. IR light
2. Shutter button
3. Photo-Sensitive Lenses
4. MICRO SD Flash (TF card) Jack
5. USB 2.0 port
6. Recording button
7. Adjustable Cameras
8. MIC
9. Talkback MIC
10. Photo Indication Light
11. LED (photoflash)
12. Talkback Speaker
13. Talkback Button
14. LED button (monitor ON/OFF)
15. Power ON/OFF button
16. Talkback port/TV port
17. fixed clamp
18. Reset button
19. Working indication light/Charging indication light
20. Monitor
21. Function button
22. Left OFF-Right ON key (IR power ON/OFF key)

